



**NOTES:**

1. TO ENSURE THAT INTERNALLY FITTED SUPPRESSORS WORK CORRECTLY:- ENSURE THAT LINE VOLTAGE IS CONNECTED TO TERMINALS MARKED 'LN' AND EACH LOAD IS CONNECTED TO TERMINALS MARKED 'NO' OR 'NC'.
2. THE DEFROST OUTPUT HAS CHANGEOVER CONTACTS. SELECT THE APPROPRIATE OUTPUT FOR THE APPLICATION.
3. THE LIQUID SOLENOID VALVE MAY BE USED AS AN ALTERNATIVE TO THE PEV OUTPUT WHEN USING A CONVENTIONAL TEV.
4. THE LCIC CONTROLLER MUST BE EARTHED TO THE CHASSIS VIA THE CONTROLLER FIXING HOLE AS SHOWN.
5. TO MEET EMC REQUIREMENTS THE CONTROLLER MUST BE INSTALLED ACCORDING TO THE INSTALLATION REQUIREMENTS SHEET FOR THIS PRODUCT.
6. INPUTS REQUIRE 'C' CONNECTED TO NEUTRAL AND THE INPUT TO 230Vac WHEN SIGNAL IS PRESENT.
7. PLANT INPUTS TO CON B MUST BE ON THE SAME PHASE AS THE SUPPLY ON CON A.  
**THIS UNIT IS NOT RATED FOR 415V**
8. FANS/HEATER OUTPUT SELECTABLE USING MAINTENANCE UNIT.
9. FOR SOFTWARE UP TO VERSION 4 THE INPUTS ARE SWAPPED.

THIS IS AN UNCONTROLLED COPY - UNLESS STAMPED WITH CONTROLLED COPY STAMP

		JTL SYSTEMS LTD 41 KINGFISHER COURT, HAMBRIDGE RD, NEWBURY BERKSHIRE: RG14 5SJ TEL: 01635 263646 FAX: 01635 263647	
ISS	DESCRIPTION	APP'D	DATE
3	ADDED CON7TS	MJK	8/97
5	ADDED NOTE 9 & SWAPPED INPUTS	MJK	3/01
4	REMOVED CON BOARDS	MJK	7/98
TITLE: CABINET CONTROLLER WIRING			
TYPE: LCIC & LCIP			
PROJ.	DRG No:	SHT	OF
LC	01770	1	1
			ISS
			5